

# **skandia**

**RemoteMaster BW600**

**Preprogrammed Universal Remote Control  
Operating Instructions**

**GB**



**GB**

- 1. Infrared Transmitter
- 2. Power Button
- 3. FOX Button
- 4. Mute Button
- 5. Device Mode Keys
- 6. Function Keys
- 7. Battery Compartment



## Table of Content

<b>How to install batteries</b> .....	<b>4</b>
<b>How to set up the URC</b> .....	<b>4</b>
FOXTEL .....	4
By Entering Device Code .....	4
By Searching Through Library .....	5
By Auto Search .....	6
<b>Operating the URC</b> .....	<b>6</b>
<b>Advanced Operation</b> .....	<b>6</b>
Volume Punch Through .....	6
Code Read Out .....	7
Master Reset .....	7
<b>Maintenance</b> .....	<b>7</b>
<b>Trouble-shooting</b> .....	<b>8</b>
<b>Device Code Library</b> .....	<b>9</b>

GB

Congratulations! Your Universal Remote Control (URC) is a state-of-the-art device which integrates many different Infra-red remote controls to deliver instant A/V control action to your fingertips.

Before operating the remote, please read thoroughly 1) descriptions of the coversheet and 2) this manual. Then, reserve them for future reference.

## HOW TO INSTALL BATTERIES

Alkaline batteries are recommended. 2 x AAA Required.

GB

1. Remove the battery cover on the back side of your URC.
2. Observe the polarity of the batteries and the "+/-" marks inside the battery compartment.
3. Insert the batteries accordingly.
4. Push the battery cover back in place.

## HOW TO SET UP THE URC

Before your URC can operate your A/V devices, you have to go through one of the following SIMPLE set up procedures to set up your URC.

- *For FOXTEL*
- *By Entering Device Code*
- *By Searching Through Library*
- *By Auto Search*

### FOXTEL

The BW600 is unique. It is unlike other URC. Foxtel has been preprogrammed into its own dedicated button. Simply push the **FOX** button to operate. No programming required. In the case of duel function the Foxtel command has been screen printed onto the remote.

### By Entering Device Code

You may set up the URC by following Device Code Entering instructions:

1. Find the appropriate DEVICE CODE in the DEVICE CODE LIST section of this instruction manual, check the 4-digit Device Code which corresponds to the brands of your A/V equipment. If there are more than ONE Device Code listed under your brand, try from the first code until you find the correct code.
2. Select a desired Device Mode (e.g. TV, if you want to set up your URC to operate your TV)
3. Press and Hold the **SET** key followed by the desired Device Mode key (e.g. **TV**), the LED indicator will light up.
4. Release both keys.
5. Use the number keys **0-9** to enter your 4-digital Device Code, the indicator should go out immediately.

*(Turn on your device (e.g. TV), try the function keys on the URC. If your device (e.g. TV) responds to your invoked function correctly, you have entered the right Device Code. Otherwise, repeat the above set up instructions with the next available Device Codes until your device (e.g. TV) responds to your invoked function, and most keys work correctly)*

**Remarks:**

- If the entered code is not correct, the LED indicator will flash TWICE and keep light on. You have to enter the correct 4-digit code again.
  - Your URC will quit the set up mode automatically after 10 seconds of idle period.
  - If you want to quit the set up mode during the set up procedures, simply press the corresponding Device Mode Key.
  - If you cannot find a correct Device Code for your equipment, see "**HOW TO SET UP THE URC – By Searching Through Library**" section
- \*\* Simply repeat the above procedures to enter the Device Codes for your VCR, SAT, CTV, STB, DVD or AMP. (Remember to press a correct Device Mode Key in Step 3 above.)

**By Searching Through Library**

If you cannot identify a correct Device Code for your equipment from the Device Code List, you may search the code through the library:

1. Turn on your device manually. (e.g. TV)
2. Select a desired Device Mode. (e.g. TV, if you want to set up your URC to operate your TV)
3. Press and Hold the **(SET)** key followed by the desired Device Mode key (e.g. **(TV)**), the LED indicator will light up.
4. Release both keys.
5. Press **(SET)** key once again and the LED should flash. (Your URC is now ready to start searching)
6. Aim your URC at your device (e.g. TV), press the "⏻" key repeatedly, slowly and patiently until the device has been turned off.
7. Once your device has been turned off, press the corresponding Device Mode key (e.g. **(TV)**) to lock in the code and the indicator should go out.

*(Turn on your device again (e.g. TV), try the function keys on the URC. If your device (e.g. TV) responds to your invoked function correctly, your URC has found the right code. Otherwise, repeat the above set up instructions for the right code, and until your device (e.g. TV) responds to your invoked function and most keys work correctly.)*

- \*\* Simply repeat the above procedures to find the codes for your VCR, DVD, DVD-R, SAT, STB or AMP. (Remember to press a correct Device Mode Key in Step 3 above.)

**Note :**

- Each time you press "⏻" key, your URC will skip to the next code and send out a POWER signal trying to turn off your device.
- If you failed to stop pressing "⏻" in time when your device has been turned off, turn on your device again immediately before the indicator of your URC goes out. Press **(SET)** key on the URC to skip backward. Repeat the step 7 above and lock in the code.

**Remarks:**

- Your URC will quit the set up mode automatically after 30 seconds of idle period.
- If you want to quit the set up mode during the set up procedures, simply press the corresponding Device Mode Key.

### **By Auto Search**

If the above 2 set up method cannot help you, your URC has been loaded with one more set up method – **Auto Search**.

GB

1. Turn on your device manually. (e.g. TV)
2. Select a desired Device Mode. (e.g. TV, if you want to set up your URC to operate your TV)
3. Press and Hold the **(SET)** key followed by the “**⏻**” key for 3 seconds until the LED indicator lights up.
4. Release both keys.
5. Aim your URC at your device (e.g. TV), your URC will send sequence of POWER signal automatically.
7. Once your device has been turned off, press the corresponding Device Mode key (e.g. **(TV)**) to lock in the code and the indicator should go out.

*(Turn on your device again (e.g. TV), try the function keys on the URC. If your device (e.g. TV) responds to your invoked function correctly, your URC has found the right code. Otherwise, repeat the above set up instructions for the right code, and until your device (e.g. TV) responds to your invoked function and most keys work correctly.)*

## **OPERATING THE URC**

### **Normal Operation**

Once you have set up the URC for your A/V equipment, it works like your original remote controls. To operate, just aim it at your equipment, press an appropriate device mode key and invoke the desired function by pressing a corresponding key on the URC. The indicator flashes during signal transmission and as confirmation of key touch.

### **Advanced Operation**

Your URC has built in with several advanced user function:

- **Volume Punch Through**
- **Code Read Out**
- **Master Reset**

#### ***Volume Punch Through***

**Volume Punch Through** allows you to operate TV's volume and mute functions without having to switch the device modes repeatedly even when your URC is in other operation modes.

#### **Volume Punch Through set up procedures**

By default, your URC has activated TV's volume punch through to the rest of the device modes. However, you can enable/disable this function by the following setting procedures:

### Punch Through Enable

1. Select a desired Device Mode (e.g. "STB", if you want to punch through TV volume control to STB mode).
2. Press and Hold the **(SET)** key followed by the desired Device Mode key (e.g. **(STB)**), the LED indicator will light up.
3. Release both keys.
4. Use the number keys **0-9** to enter 9-0-1, the indicator should go out immediately.

### Punch Through Disable

1. Select a desired Device Mode (e.g. "STB", if you do not want TV volume to punch through STB mode).
2. Press and Hold the **(SET)** key followed by the desired Device Mode key (e.g. **(STB)**), the LED indicator will light up.
3. Release both keys.
4. Use the number keys **0-9** to enter 9-0-2, the indicator should go out immediately.

GB

### Code Read Out

**Code Read Out** allows you to check your input 4-digit device code. The procedure is simple as below:

1. Press the selected Device Mode key (e.g. **(TV)**) once.
2. Press and Hold **(SET)** key and numeric key **1** to see the LED flashes time for the 1st digit device code and release all buttons
3. Press and Hold **(SET)** key and numeric key **2** to see the LED flashes time for the 2nd digit device code and release all buttons
4. Press and Hold **(SET)** key and numeric key **3** to see the LED flashes time for the 3rd digit device code and release all buttons
5. Press and Hold **(SET)** key and numeric key **4** to see the LED flashes time for the 4th digit device code and release all buttons

### Master Reset

**Master Reset** allows you to reset your URC to its factory default state. (After **Master Reset**, you have to set up the URC from beginning. Before you do this, please make sure it is really necessary.)

1. Press and Hold **(SET)** key and **(TV)** key, the LED indicator will light up.
2. Then, use the number keys **0-9** to enter 9-9-0, the indicator should flash THREE times and your URC has been reset back to factory default.

## MAINTENANCE

1. Do not expose your URC to dust, strong sunlight, humidity, high temperature or mechanical shock.
2. Do not use old and new batteries together as old batteries tend to leak.
3. Do not use corrosive or abrasive cleaners on your URC.
4. Keep the unit always dust free by wiping it only with soft and dry cloth.
5. Do not disassemble your URC, it contains no user-serviceable parts.

## TROUBLE-SHOOTING

**Q. My URC does not work at all!**

- A. Check your AV device, if the device's main switch is turned off, your URC could not operate your device.
- A. Check whether your batteries are inserted properly and are in correct +/- marks.
- A. Check whether you have pressed the corresponding device mode key for your device.
- A. If the batteries are low, replace the batteries.

GB

**Q. If several Device Codes are listed under the brand of my AV device, how can I select the correct Device Code?**

- A. To locate the correct Device Code for your AV device, test the code one by one until most keys work properly.

**Q. My AV equipment responds only to some of the commands.**

- A. You have set a code for which only some commands work properly but some do not. Try other codes until most keys work properly.

**Still having problems.**

Web support [www.antennawarehouse.com.au/remotemaster](http://www.antennawarehouse.com.au/remotemaster)

Phone support 1300 788 466



## DEVICE CODE LIBRARY

TV				BASIC LINE	1009	1011	1051
TV/VCR Combo					1245		
Model	Code						
ACER	1080			BASTIDE	1003		
ACME	1013			BAUR	1076	1118	1132
ADA	1008				1141	1169	
ADC	1008	1012		BEKO	1007	1034	1042
ADMIRAL	1001	1002	1019		1083	1095	1244
	1047	1108		BEON	1051	1169	
ADYSON	1003			BEST	1113		
AGAZI	1002			BESTAR	1051	1245	
AGB	1123			BINATONE	1003		
AIKO	1003	1004	1009	BLACK DIAMOND	1171		
AIWA	1184	1242	1248	BLACK PANTHER LINE	1245		
AKAI	1004	1006	1008	BLACK STAR	1129		
	1009	1011	1051	BLAUPUNKT	1008	1022	1100
	1061	1068	1069		1117	1135	1202
	1086	1088	1133	BLUE SKY	1011	1073	1156
	1141	1169	1200	BLUE STAR	1120		
	1219			BLOOM	1015		
AKIBA	1011			BONDSTEC	1129		
AKURA	1002	1009	1011	BOOTS	1003		
	1071	1074	1169	BPL	1120		
ALBA	1003	1009	1011	BRANDT	1022	1036	1045
	1027	1028	1047		1046	1126	1127
	1062	1068	1083		1139		
	1162	1169	1245	BRION VEGA	1000	1051	1169
	1248			BRITANNIA	1003		
ALBIRAL	1037			BROKSONIC	1277		
ALKOS	1164			BRUNS	1000	1007	
ALLORGAN	1026	1157		BSR	1026	1131	
ALLSTAR	1051			BTC	1011		
ALTUS	1042			BUSH	1009	1011	1019
AMPLIVISION	1003				1024	1027	1028
AMSTRAD	1002	1009	1011		1032	1039	1051
	1013	1030	1068		1062	1068	1107
	1069	1071	1074		1115	1120	1131
	1108	1123			1132	1139	1167
ANAM	1009	1065	1109		1169	1205	1245
ANGLO	1009			CAPSONIC	1002		
ANITECH	1002	1009	1043	CARREFOUR	1027		
	1109			CASCADE	1009		
ANSONIC	1009	1014		CATHAY	1051		
AOC	1134			CENTRUM	1168	1205	
ARC EN CIEL	1045	1126	1139	CENTURION	1051	1169	
ARCAM	1003			CENTURY	1000		
ARISTONA	1051	1169		CGE	1043	1047	1129
ARTHUR MARTIN	1158				1131		
ASA	1000	1016	1017	CIMLINE	1009	1028	
	1018	1021	1110	CITY	1009		
ASBERG	1043	1051		CLARIVOX	1037	1169	
ASTRA	1009			CLATRONIC	1002	1003	1009
ASUKA	1002	1003	1011		1011	1030	1043
ATLANTIC	1003	1051	1157	COMBITECH	1051	1083	1129
	1169			CONCORDE	1248		
ATORI	1009			CONDOR	1009		
AUDIOSONIC	1003	1009	1011		1003	1051	1083
	1051	1090	1139		1198	1245	
	1157	1169		CONRAC	1038	1224	
AUDIOTON	1003			CONTEC	1003	1009	1027
AUSIND	1043				1029	1030	
AUTOVOX	1000	1002	1003	CONTINENTAL EDISON	1022	1036	1045
	1043	1101	1125		1111	1126	1139
	1157				1046		
B&O	1000	1199		COSMEL	1009		
BAIRD	1111	1139	1245	CPRTEC	1156		
BARCO	1112			CROSLEY	1000	1043	1129
					1131		

CROWN	1009	1043	1047	DUAL	1002	1003	1009
	1051	1121	1169		1042	1044	1047
	1183	1245			1061	1063	1067
CS ELECTRONICS	1003	1011	1129		1068	1089	1103
CTC	1129				1107	1115	1125
CTC CLATRONIC	1014				1126	1127	1131
CYBERCOM	1002	1009	1026		1138	1139	1154
	1038	1042	1044		1160	1168	1169
	1047	1061	1063		1171	1177	1206
	1067	1068	1103		1207	1208	1210
	1107	1115	1127		1228	1242	1248
	1154	1168	1169		1275	1276	1279
	1171	1177	1185	DUAL-TEC	1003	1009	1131
	1205	1206	1207	DUMONT	1000	1003	1014
	1208	1209	1210		1017	1018	
	1228	1242	1248	DURABRAND	1228	1240	1266
	1275	1279			1267	1268	1269
CYBERMAXX	1002	1009	1015		1275		
	1038	1042	1044	DUX	1169		
	1047	1048	1049	DYNATRON	1051	1169	
	1061	1063	1067	ELBE	1037	1108	1157
	1068	1087	1103	ELCIT	1000		
	1107	1115	1127	ELECTRO TECH	1009		
	1154	1155	1168	ELEKTA	1120		
	1169	1170	1171	ELIN	1003	1016	1018
	1177	1185	1200		1051	1169	
	1205	1206	1207	ELITE	1011	1051	
	1208	1209	1210	ELMAN	1014	1131	
	1211	1218	1228	ELTA	1009		
	1229	1242	1248	EMERSON	1000	1127	1141
	1270	1275	1276	ERAE	1272		
	1278	1279		ERRES	1051	1169	
CYBERTRON	1011			ESC	1245		
CYTRON	1002	1009	1015	ETRON	1009		
	1038	1042	1044	EURO-FEEL	1002		
	1047	1048	1049	EUROLINE	1088	1149	1169
	1061	1063	1067	EUROMANN	1002	1003	1051
	1068	1087	1103	EUROPHON	1003	1014	1051
	1107	1115	1127		1123	1131	
	1154	1155	1168	EXPERT	1157		
	1169	1170	1171	FAIRTEC	1073	1156	1190
	1177	1185	1200		1204		
	1205	1206	1207	FENNER	1009	1115	
	1208	1209	1210	FERGUSON	1035	1036	1037
	1211	1218	1228		1050	1052	1111
	1229	1242	1248		1127	1163	1166
	1270	1275	1276		1169		
	1278	1279		FIDELITY	1003	1019	1068
DAEWOO	1003	1009	1051		1074	1096	
	1094	1115	1191	FINLANDIA	1006	1019	1110
	1245				1128		
DAINICHI	1011			FINLUX	1000	1003	1004
DANSAI	1002	1051	1169		1014	1016	1017
DANTAX	1034	1088	1113		1018	1042	1043
	1161	1169	1171		1051	1061	1063
DATSURA	1121				1087	1110	1123
DAYTON	1009				1131	1157	1167
DAYTRON	1245				1169		
DCE	1042	1205		FIRSTLINE	1003	1009	1026
DE GRAAF	1006	1019	1033		1051	1062	1129
DECCA	1003	1004	1030		1156		
	1051	1123	1169	FISHER	1000	1003	1006
DECCACOLOR	1015				1018	1027	1029
DELL	1025				1040	1083	1131
DESMET	1051	1169		FLINT	1051	1113	
DIGITOR	1227	1228		FORMENTI	1000	1001	1003
DISNEY	1148				1043	1125	1131
DIXI	1009	1051	1169		1133	1169	
DTS	1009			FORTRESS	1000	1001	

FRONTECH	1002	1009	1019	HORNYPHON	1051		
	1021	1068	1118	HOSHAI	1011		
	1120	1129		HUANYU	1003	1115	
FUJITSU	1004	1116	1157	HYGASHI	1003		
FUNAI	1002	1026		HYPER	1003	1009	1129
GALAXY	1047	1083			1131		
GBC	1009	1027	1131	HYPSON	1002	1003	1051
GEC	1003	1004	1041		1120	1169	
	1051	1123	1132	HYUNDAI	1010		
	1141	1169		ICE	1002	1003	1009
GELOSO	1009	1019	1131		1011	1051	1068
GENERAL TECHNIC	1009	1248		IYAMA	1193		
GENEXXA	1011	1021	1051	IMPERIAL	1021	1043	1047
GERICOM	1049	1244	1249		1051	1083	1129
	1251				1131		
GOLDSTAR	1003	1009	1012	INDESIT	1024	1101	
	1019	1051	1084	INDIANA	1051	1169	
	1093	1129	1131	INGELEN	1021		
	1169	1171	1261	INGERSOL	1009		
GOODMANS	1002	1004	1009	INNO HIT	1003	1004	1009
	1027	1028	1051		1011	1051	1093
	1068	1093	1111		1123	1169	1245
	1115	1127	1169	INNOVATION	1002	1009	1061
	1171	1241	1245		1067	1068	1103
GORENJE	1083			1107	1111	1115	
GPM	1011			1154	1168	1169	
GRAETZ	1021	1141	1142		1171	1177	1242
GRANADA	1003	1004	1006		1248		
	1019	1027	1031	INTERBUY	1009	1109	1129
	1040	1043	1051	INTERFUNK	1000	1021	1051
	1054	1064	1123		1129	1139	1141
	1127	1128	1133		1169		
	1138	1169		INTERTRONIC	1278		
GRUNDIG	1008	1017	1043	INTERVISION	1002	1003	1014
	1091	1101	1114		1109		
	1117	1135	1136	IRRADIO	1009	1011	1051
GRANDIN	1009	1011	1120		1068	1169	
	1169	1245		ISUKAI	1011		
	1228	1279		ITC	1003	1131	
H&B	1015	1042	1095	ITS	1011	1051	1068
HB	1168	1233	1253		1120		
	1263	1272		ITT	1009	1021	1061
HAAZ	1228				1031	1132	1133
HALIFAX	1002	1003			1141	1142	1143
HAMPTON	1003			ITT/NOKIA	1021	1133	1142
HANSEATIC	1003	1007	1009	ITV	1009	1088	1169
	1026	1027	1051		1171	1245	
	1083	1118	1131	JEC	1164		
	1141	1169		JVC	1027	1051	1053
HANSOL	1254			1068			
HANTAREX	1009	1123		KAISUI	1003	1009	1011
HARWOOD	1171				1120		
HCM	1002	1003	1009	KAMOSONIC	1003		
	1074	1120		KAMP	1003		
HIFIVOX	1139			KAPSCH	1021	1157	
HINARI	1006	1009	1011	KARCHER	1003	1009	1016
	1027	1043	1051		1037	1169	
	1137	1169	1171	KENDO	1014	1019	1028
	1248				1108	1245	
HISAWA	1011	1113	1120	KENNEDY	1131	1157	
HISENSE	1070	1073	1156	KINGSLEY	1003		
	1179	1190	1192	KING TV	1015		
	1204			KNEISSEL	1174		
	1003	1004	1016	KOLSTER	1051		
	1019	1021	1023	KONKA	1011	1047	1068
	1027	1033	1041		1229		
	1045	1046	1047	KORPEL	1051	1169	
	1085	1118	1123	KORTING	1000		
	1131	1133	1134	KOYODA	1009		
	1138	1139	1140	KTV	1003		
	1141	1142	1144	KURO	1121		
	1153	1213	1260				

KYOTO	1037			MATSUSHITA	1065		
LENCO	1009	1245		MAXMEDIA	1115		
LENOIR	1003	1009		MCMICHAEL	1041		
LESA	1129			MEDIATOR	1051	1169	
LEYCO	1002	1004	1026	MEDION	1002	1009	1015
	1051	1169			1038	1042	1044
LG	1003	1009	1019		1047	1049	1061
	1051	1084	1088		1063	1067	1068
	1093	1119	1129		1087	1103	1107
	1131	1149	1169		1115	1127	1148
	1171	1261			1154	1155	1168
LIESENK	1169				1169	1170	1171
LIFE	1002	1009	1061		1175	1177	1185
	1067	1068	1103		1200	1205	1206
	1107	1111	1115		1207	1208	1209
	1154	1168	1169		1210	1211	1218
	1171	1177	1205		1222	1224	1228
	1242	1291			1229	1242	1248
LIFETEC	1002	1009	1015		1258	1259	1270
	1042	1044	1047		1273	1274	1275
	1048	1049	1061		1276	1278	1279
	1063	1067	1068	MELECTRONIC	1003	1009	1016
	1087	1103	1107		1018	1021	1036
	1115	1127	1138		1051	1068	1109
	1154	1155	1168		1110	1115	1139
	1169	1170	1171		1169		
	1177	1185	1205	MEMOREX	1009	1277	
	1206	1207	1208	MEMPHIS	1004	1009	
	1209	1210	1211	METZ	1000	1038	1058
	1218	1228	1229		1075	1107	1135
	1242	1248	1270		1151	1152	1201
	1275	1276	1278		1205	1221	
	1279			MICROMAXX	1002	1009	1015
LOEWE	1000	1051	1097		1038	1042	1044
	1098	1169	1220		1047	1048	1049
LOGIK	1030				1061	1063	1067
LS ELECTRONIK	1042				1068	1087	1103
LUMA	1019	1141	1157		1107	1115	1127
	1169				1154	1155	1168
LUMATRON	1002	1019	1051		1169	1170	1171
	1074	1088	1107		1177	1185	1200
	1141	1157	1169		1205	1206	1207
	1171	1245			1208	1209	1210
LUX MAY	1051				1211	1218	1228
LUXOR	1003	1019	1047		1229	1242	1248
	1077	1093	1132		1270	1275	1276
	1138	1141			1278	1279	
M+P	1133			MICROSTAR	1002	1009	1015
MAGNADYNE	1014	1129	1131		1038	1042	1044
	1169	1000	1123		1047	1048	1049
MAGNAFON	1003	1014	1043		1061	1063	1067
	1123				1068	1087	1103
MAGNUM	1002	1009	1061		1107	1115	1127
	1067	1068	1103		1148	1154	1155
	1107	1111	1115		1168	1169	1170
	1154	1168	1169		1171	1177	1185
	1171	1177	1200		1200	1205	1206
	1242				1207	1208	1209
MANDOR	1002				1210	1211	1218
MANESTH	1002	1003	1028		1228	1229	1242
	1051	1169			1248	1270	1275
MARANTZ	1051	1150	1169		1276	1278	1279
MARELLI	1000				1101	1135	1258
MARK	1051	1169		MINERVA	1101	1135	1258
MATSUI	1003	1004	1009	MINOKA	1051		
	1013	1019	1026	MITSUBISHI	1000	1027	1030
	1027	1028	1030		1051	1054	1057
	1051	1062	1068		1060	1098	1101
	1091	1099	1101		1135	1205	
	1113	1123	1147	MIVAR	1003	1043	1055
	1164	1169	1173		1083	1093	1123
	1180	1248					

MOTION	1043			PANASONIC	1021	1064	1065
MT LOGIC	1090				1067	1072	1101
MTC	1132				1124	1141	1142
MULTI SYSTEM	1169				1151	1152	1186
MULTITECH	1003	1009	1014		1197		
	1019	1027	1043	PATHE CINEMA	1003	1037	1083
	1045	1129	1131		1131		
	1169			PATHE MARCONI	1022	1037	1045
MURPHY	1003	1018	1133		1046	1126	1139
NAD	1141			PAUSA	1009		
NAIKO	1099			PERDIO	1004		
NAONIS	1019	1108		PHILCO	1000	1043	1047
NATIONAL	1064	1101			1129	1131	
NEC	1027	1056	1081	PHILHARMONIC	1003		
	1150	1185		PHILIPS	1000	1003	1020
NECKERMANN	1000	1003	1008		1041	1043	1051
	1019	1022	1051		1083	1088	1089
	1083	1118	1132		1111	1115	1131
	1169				1141	1154	1169
NEI	1051	1068	1113		1181	1200	1202
	1169				1217		
NEOVIA	1254			PHOCUS	1042	1095	1244
NESCO	1129			PHOENIX	1000	1051	1169
NEW WORLD	1011			PHONOLA	1000	1051	1169
NEWTECH	1009	1051		PIONEER	1010	1021	1036
NEXIUS	1015				1051	1139	1145
NICAMAGIC	1003				1150	1169	1178
NIKKAI	1002	1003	1004	PLANTRON	1002	1051	
	1011	1051	1164	POPPY	1009		
	1169			PORTLAND	1245		
NOBLIKO	1003	1014	1043	PRANDONI-PRINCE	1019	1123	1141
NOGAMATIC	1139			PRECISION	1003		
NOKIA	1021	1031	1061	PRIMA	1009	1021	
	1063	1077	1132	PRINZ	1047		
	1133	1141	1142	PRO2	1002	1009	1015
	1143				1038	1042	1044
NORDMENDE	1000	1021	1024		1047	1048	1049
	1036	1045	1046		1061	1063	1067
	1051	1111	1126		1068	1087	1103
	1127	1139	1225		1107	1115	1127
	1230	1231			1154	1155	1168
NORDVISION	1169				1169	1170	1171
OCEANIC	1003	1021	1141		1177	1185	1200
	1142	1239	1263		1205	1206	1207
OKANO	1083				1208	1209	1210
ONWA	1069				1211	1218	1228
ORBIT	1051				1229	1242	1248
ORION	1009	1013	1026		1270	1275	1276
	1028	1030	1051	PROFEX	1278	1279	
	1062	1075	1099	PROFILO	1009	1043	1141
	1123	1142	1147	PROFI-TRONIC	1171		
	1154	1159	1169	PROLINE	1051		
	1171	1212	1241	PROSONIC	1004	1051	1062
	1248	1277			1003	1015	1042
ORMOND	1205				1068	1088	1107
OSAKI	1002	1003	1004		1161	1169	1200
	1011	1074			1245		
OSO	1011			PROTECH	1002	1003	1009
OSUME	1004	1029			1014	1051	1113
OTTO VERSAND	1001	1003	1008		1129	1131	1132
	1027	1051	1076		1169		
	1111	1118	1120	PROVIEW	1175	1273	1274
	1121	1131	1132	PROVISION	1015	1169	1171
	1139	1141	1169	PYE	1051	1068	1169
	1203	1204		PYMI	1009		
PACKARD BELL	1003			QUADRO	1205		
PAEL	1003			QUASAR	1129		
PALLADIUM	1003	1012	1083	QUELLE	1002	1003	1016
PANAMA	1002	1003	1009		1017	1018	1022
					1026	1030	1051
					1129	1131	1135
					1141	1169	1205

QUESTA	1027			SENTRA	1164		
RADIOLA	1051	1169		SHARP	1001	1005	1027
RADIOMARELLI	1000	1123	1129		1029	1059	1187
RADIONETTE	1016	1018			1188		
RADIOTONE	1007	1051		SHORAI	1026		
RANK	1017	1027		SIAREM	1000	1014	1123
RBM	1017				1131		
RCA	1031			SICATEL	1037		
REDIFFUSION	1141			SIEMENS	1008	1022	1029
REVOX	1051	1169			1135	1200	
REX	1002	1019	1108	SIERRA	1051		
	1021	1157		SIESTA	1160		
RFT	1000	1007		SILVER	1027		
R-LINE	1051	1169		SINGER	1000	1014	1129
ROADSTAR	1002	1009	1011		1131	1228	
	1245			SINUDYNE	1000	1013	1014
ROBOTRON	1000				1015	1026	1028
RTF	1000				1075	1131	1169
SABA	1000	1021	1036	SKANTIC	1021	1138	
	1045	1046	1111	SKYMASTER	1016		
	1123	1126	1127	SKYWORTH	1228		
	1139	1141	1142	SLIDING	1015		
	1245	1248		SOLAVOX	1021	1092	
SACCS	1037			SONITRON	1016	1031	
SAISHO	1002	1003	1009	SONOKO	1002	1003	1009
	1013	1028	1030		1051	1169	1245
	1123	1248		SONOLOR	1006	1021	
SALORA	1019	1021	1031	SONTEC	1051	1160	1169
	1047	1061	1093	SONY	1004	1009	1027
	1107	1108	1118		1029	1030	1076
	1121	1128	1131		1106	1127	1130
	1132	1138	1141		1165	1182	1183
SAMBERS	1014	1043	1123	SOUND&VISION	1011	1014	
	1169	1216		SOUNDWAVE	1051	1169	
SAMSUNG	1002	1003	1004	STANDARD	1003	1009	1011
	1009	1030	1051		1051	1245	
	1083	1090	1093	STARLIGHT	1169		
	1104	1105	1160	STENWAY	1120		
	1172	1281		STERN	1019	1021	1157
SABDRA	1003	1009		SUNGOO	1192	1206	1258
SANSUI	1051	1277		SUNKAI	1009	1026	1062
SANYO	1003	1004	1006	SUNWOOD	1009	1051	
	1016	1018	1027	SUPERLA	1003		
	1029	1030	1031	SUPERTECH	1118		
	1040	1043	1083	SUPRA	1009		
	1127	1131	1160	SUSUMU	1011		
SAVILLE	1248			SUTRON	1009		
SBR	1041	1169		SYDNEY	1003		
SCHAUB LORENZ	1015	1021	1042	SYSLINE	1169		
	1095	1141	1142	TANDBERG	1026	1157	
	1168	1202	1205	TANDY	1001	1003	1004
	1232	1233	1234		1011	1021	1133
	1235	1236	1237	TARGA	1185	1255	1271
	1253	1263	1272		1272		
SCHNEIDER	1003	1011	1051	TASHIKO	1003	1019	1027
	1068	1071	1125		1041	1056	1128
	1131	1139	1160	TATUNG	1003	1004	1051
	1169	1177	1245		1123	1169	
	1264			TCM	1002	1009	1038
SCHWAIGER	1247				1042	1044	1047
SEG	1002	1003	1009		1061	1063	1067
	1014	1027	1043		1068	1103	1107
	1088	1129	1131		1115	1127	1154
	1168	1169	1171		1168	1169	1171
	1205	1259			1177	1185	1194
SEI-SINUDYNE	1000	1013	1014		1205	1206	1207
	1021	1026	1075		1208	1209	1210
	1123				1211	1228	1238
SEITECH	1015				1242	1248	1256
SELECO	1019	1021	1027		1258	1270	1275
	1108	1131	1157		1276	1279	
SENCORA	1009						

TEC	1003	1009	1129		1129	1131	1138
	1131	1133			1168	1169	1171
TECHNICS	1065				1195	1205	1215
TECHNISAT	1088	1099	1154		1259		
TECHNISSON	1042			VEXA	1009	1169	
TELEAVIA	1022	1036	1045	VICTOR	1027	1051	1065
	1111	1126	1139	VIDEO SYSTEM	1051		
TELEFUNKEN	1022	1035	1036	VIDEOCON	1196		
	1050	1051	1052	VIDEOLIQUE	1003	1011	
	1078	1079	1101	VIDEON	1248		
	1102	1108	1111	VIDEOSAT	1129		
	1126	1127	1139	VISIOLA	1003		
	1163	1166	1190	VISION	1051		
TELETECH	1009	1088	1113	VISOREX	1096		
	1129	1169		VISTAR	1133		
TELETON	1003	1118	1132	VIVAX	1015	1042	1267
	1157			VORTEC	1051	1169	
TENSAI	1011	1018	1026	VOXSON	1000	1019	1021
	1051	1168			1043	1051	1108
TESMET	1051			WALTHAM	1003	1037	1133
TEVION	1002	1009	1015		1138		
	1038	1042	1044	WATSON	1051	1169	
	1047	1048	1049	WATT RADIO	1003	1014	1037
	1061	1063	1067		1131		
	1068	1087	1103	WEGA	1000	1027	
	1107	1115	1127	WEGAVOX	1015		
	1154	1155	1168	WELLTECH	1042		
	1169	1170	1171	WELTBlick	1051	1169	
	1177	1185	1200	WESTON	1131		
	1205	1206	1207	WHARFEDALE	1099		
	1208	1209	1210	WHITE WESTINGHOUSE	1003	1014	1043
	1211	1214	1218		1169		
	1228	1229	1242	WORLD OF VISION	1252		
	1244	1248	1257	YAKUMO	1262		
	1258	1270	1275	YALOS	1000		
	1276	1278	1279	YINHE	1223		
TEXET	1003			YOKO	1002	1003	1009
THOMSON	1003	1022	1036		1011	1051	1169
	1045	1046	1050	YORX	1011		
	1051	1052	1101	ZANUSSI	1019	1108	1157
	1102	1111	1126				
	1127	1139	1163				
	1166	1176	1185				
	1226	1245					
THORN	1004	1018	1035	<b>Model</b>	<b>Code</b>		
	1037	1054	1111	AIWA	2000 2001 2003		
	1127	1141	1164		2018 2025 2059		
	1169				2061		
TOKAI	1004	1051		AKAI	2006 2007 2008		
TOKYO	1003				2009 2061 2066		
TOMASHI	1120				2073 2091		
TOSHIBA	1017	1027	1082	AKIBA	2044		
	1117	1146	1150	AKURA	2014 2044 2061		
	1164	1189	1277	ALBA	2003 2015 2016		
TOWADA	1021	1131			2017 2018 2020		
TRIUMPH	1013	1082	1123		2044		
UHER	1021	1043	1051	ALLORGAN	2077		
	1157			AMBASSADOR	2020		
ULTRAVOX	1000	1003	1014	AMSTRAD	2001 2022 2023		
	1129	1131	1133	ANITECH	2044		
UNITED	1088	1169		APEX	2105		
UNITED QUICK STAR	1245			ASA	2025 2026		
UNIVERSUM	1002	1016	1018	ASUKA	2001 2025 2026		
	1051	1061	1169		2044		
	1083	1102	1110	BAIRD	2001 2007 2015		
	1122	1129	1131		2027 2028 2061		
	1143			BASIC LINE	2003 2015 2020		
UNIVOX	1037				2044		
VESTEL	1006	1019	1021	BAUR	2026 2032		
	1051	1083	1092	BESTAR	2015 2020		
	1103	1107	1118	BLACK PANTHER LINE	2015		

BLAUPUNKT	2026	2029	2031	GOLDHAND	2044		
	2032	2040	2075	GOLDSTAR	2001	2025	2030
	2087			GOODMANS	2001	2015	2020
BLUESKY	2018				2025	2028	2044
BONDSTEC	2020				2051	2050	
BRANDT	2069	2071		GO-VIDEO	2092	2095	2110
BROKSONIC	2045	2107		GRAETZ	2027	2061	
BUSH	2015	2016	2017	GRANADA	2240	2257	2258
	2018	2033	2044		2266	2271	
	2056			GRANDIN	2001	2015	2020
CATRON	2020				2025	2044	
CGE	2000	2061		GRUNDIG	2005	2013	2026
CIMLINE	2033	2044			2029	2032	2039
CINEVISION	2025				2040	2041	2042
CLATRONIC	2020				2044	2054	2055
COMBITTECH	2018				2056	2058	2081
CONDOR	2015	2020		HAAZ	2003		
CROWN	2015	2020	2044	HANSEATIC	2025	2026	
CYBERCOM	2003	2018	2025	HCM	2044	2056	
	2031	2038	2059	HINARI	2003	2018	2044
	2077	2082	2092		2056	2067	
	2100	2101		HISAWA	2003		
CYBERMAXX	2003	2018	2025	HITACHI	2001	2026	2035
	2031	2038	2059		2037	2061	2097
	2077	2082	2092	HYPSON	2003	2044	
	2100	2101		IMPEGO	2020		
CYTRON	2003	2018	2025	IMPERIAL	2001		
	2031	2038	2059	INNO HIT	2015	2020	2026
	2077	2082	2092	INNOVATION	2003	2018	2031
	2100	2101			2059	2077	
DAEWOO	2015	2020	2034	INTERBUY	2025		
	2043	2082	2100	INTERFUNK	2026	2027	
DANSAI	2044			INTERVISION	2001		
DANTAX	2003			IRRADIO	2025	2044	
DAYTRON	2015			ITT	2007	2027	2060
DE GRAAF	2026	2035			2061		
DECCA	2001	2026	2061	ITV	2015	2025	
DUAL	2003	2018	2025	JVC	2061	2062	2063
	2026	2031	2059		2098		
	2061	2077	2082	KAISUI	2044		
	2092	2100	2101	KARCHER	2026		
DUMONT	2001	2026	2027	KENDO	2003	2006	2007
	2035				2015	2020	2034
	2044				2066		
ELTA	2001	2025	2067	KENWOOD	2061		
EMERSON	2093			KORPEL	2044		
ESC	2015			LENCO	2015		
ETZUKO	2044			LEYCO	2044		
FERGUSON	2028	2040	2046	LG	2001	2025	2030
	2049	2061	2062		2102		
	2071			LIFE	2025	2059	
FIDELITY	2001	2077		LIFETEC	2003	2018	2025
FINLANDIA	2026	2027	2035		2031	2038	2059
FINLUX	2001	2007	2027		2077	2082	2092
	2026	2035	2061		2100	2101	
	2064			LOEWE	2025	2026	2031
FIRSTLINE	2003	2025	2034		2036	2040	2087
	2035	2044	2064	LOGIK	2044		
FISHER	2027	2047		LUMATRON	2015	2043	
FLINT	2003			LUXOR	2007	2027	2049
FORMENTI-PHOENIX	2026				2064		
FRONTECH	2020			MAGNASONIC	2027		
FUJITSU	2001			MAGNAVOX	2053	2103	
FUNAI	2001	2093		MAGNUM	2059		
GALAXY	2001			MANESTH	2034	2044	
GBC	2020	2044		MARANTZ	2026	2040	2049
GEC	2026			MATSUI	2003	2018	2025
GELOSO	2044				2067		
GENERAL	2020			MEDIATOR	2026		
GENERAL TECHNIC	2003	2018	2031				
	2077						



MEDION	2003	2018	2025	QUELLE	2001	2026	2027
	2031	2038	2059		2032	2040	2067
	2077	2082	2092	RADIOLA	2026		
	2100	2101		REX	2061		
MELECTRONIC	2001			RFT	2020	2026	
MEMOREX	2001	2010	2025	ROADSTAR	2015	2025	2044
	2027	2044	2047	SABA	2015	2049	2061
MEMPHIS	2044				2069	2071	2086
METZ	2031	2032	2036	SAISHO	2003	2018	2044
	2040	2042	2087		2067		
MICROMAXX	2003	2018	2025	SALORA	2007	2027	2060
	2031	2038	2059		2064		
	2077	2082	2092	SAMSUNG	2077	2078	2092
	2100	2101			2106		
MICROSTAR	2003	2018	2025	SAMURAI	2020		
	2031	2038	2059	SANSUI	2014	2061	2062
	2077	2082	2092		2104		
	2100	2101		SANYO	2027	2047	2052
	2001			SAVILLE	2018		
MIGRO	2032	2040		SBR	2026		
MINERVA	2001	2026	2057	SCHAUB LORENZ	2001	2007	2027
MITSUBISHI	2062	2064			2061		
MULTITECH	2001	2020	2026	SCHNEIDER	2001	2003	2015
	2044				2020	2025	2026
MURPHY	2001				2033	2034	2044
NATIONAL	2029	2031		SEG	2044	2082	
NEC	2061	2062	2065	SEI-SINUDYNE	2026		
NECKERMANN	2026	2061	2067	SELECO	2061		
NEI	2026			SENTRA	2020		
NESCO	2044			SENTRON	2044		
NIKKAI	2020	2068		SHARP	2010	2011	2049
NOKIA	2007	2010	2027		2090		
	2060	2061	2066	SHINTOM	2027	2044	
	2073			SHIVAKI	2025		
NORDMENDE	2061	2062	2069	SIEMENS	2025	2027	2032
	2071				2040		
OCEANIC	2001	2010	2061	SILVA	2025		
OKANO	2003	2066		SILVERCREST	2025		
ORION	2003	2004	2016	SINUDYNE	2026		
	2018	2051	2067	SOLAVOX	2020		
	2070			SONOKO	2015		
ORSON	2001			SONOLOR	2010		
OSAKI	2001	2025	2044	SONTEC	2025		
OTTO VERSAND	2026			SONY	2002	2019	2021
PALLADIUM	2025	2040	2044		2024	2026	2074
	2061	2066			2075	2079	2099
PANASONIC	2029	2031	2036	STANDARD	2015		
	2080	2084	2087	STRONG	2014		
	2109			SUNKAI	2003		
PATHE CINEMA	2067			SUNSTAR	2001		
PATHE MARCONI	2061			SUNTRONIC	2001		
PENTAX	2035			SUNWOOD	2044		
PERDIO	2001			SYLVANIA	2001	2093	
PHILCO	2065			TAISHO	2003		
PHILIPS	2005	2012	2026	TANDBERG	2032		
	2040	2053	2054	TARGA	2025	2102	2111
	2058	2061	2081	TASHIKO	2001	2010	
	2089	2108		TATUNG	2001	2026	2061
PHONOLA	2026			TCM	2003	2018	2025
PIONEER	2026	2062	2112		2031	2038	2059
POLAROID	2105				2077	2082	2092
PORTLAND	2015	2020			2096	2100	2101
PRINZ	2001			TEC	2020		
PRO2	2003	2018	2025	TECHNICS	2029	2031	
	2031	2038	2059	TELEAVIA	2061		
	2077	2082	2092	TELEFUNKEN	2048	2061	2062
	2100	2101			2063	2069	2071
PROFEX	2044				2072	2085	2086
PROLINE	2001	2056		TENOSAL	2044		
PROSONIC	2003	2015		TENSAI	2001	2025	2044
PYE	2026						
QUARTZ	2027						

TEVION	2003	2077	2031	ASTRA	3014	3023	3025
	2038	2082	2025		3026	3078	
	2018	2059	2092	ASTRO	3002	3004	3022
	2100	2101			3033	3133	
THOMSON	2012	2015	2062	AUDIOTON	3002	3046	
	2061	2063	2071	AURORA	3165		
	2085	2086	2088	AUSTAR	3200	3201	3165
THORN	2027	2061	2067		3259	4007	4030
TIVO	2012			AXIS	3010	3022	3026
TOKAI	2025	2044			3042		
TONSAI	2044			BARCOM	3018		
TOSHIBA	2026	2034	2061	BEST	3018	3022	
	2064	2082	2083	BLAUPUNKT	3033		
	2094			BMB	4019		
TOWADA	2044			BOCA	3014	3078	
TOWIKA	2044			BRAIN WAVE	3037	3115	3213
TRIUMPH	2067				5017		
TVA	2020			BRANDT	3129	3130	3131
UHER	2025				3138		
UNITED QUICK STAR	2015			BSKYB	3119	3148	5031
UNIVERSUM	2001	2005	2007	BT	4013		
	2009	2022	2025	BT SATELLITE	3138		
	2026	2032	2040	BUSH	3005	3084	3126
	2058	2081			5000	5001	5013
VICTOR	2062	2063			5041	5148	
VIDEON	2003	2018	2031	CABLE AND WIRELESS	4018		
	2077			CABLECRYPT	4005		
WELTBlick	2025			CABLETIME	4000	4001	4002
YAMISHI	2044			CABLE PLUS	4005		
YOKAN	2044			CANAL+	3133	3163	5017
YOKO	2020	2025	2044		5032		
ZENITH	2025			CANAL DIGITAL	3292	3293	3295

## SAT/CTV/

## DVB-T Digital TV STB/

## Broadband/Axiliary STB/

## HDD Video Recorder

Model	Code						
@SAT	3227						
@SKY	3218						
ADECQ	3289	5131	5151				
AKAI	3117						
ALBA	3000	3002	3126				
	3084	5013	5040				
ALICE TV	5094						
ALDES	3004	3008					
ALLSAT	3005	3117	3046				
ALLSONIC	3003	3022					
AMPERE	3016						
AMSTRAD	3107	3010	3011				
	3012	3014	3119				
	3148	5031					
ANKARO	3003	3018	3022				
ANTTRON	3000	3002					
APOLLO	3000						
ARCOM	3239	3242	5139				
ARCON	3010	3016	3018				
	3047	3224	3230				
	3231	3232	5087				
ARENA	3257						
ARION	3269	5137					
ARMSTRONG	3014						
ARNION	3227						
ASAT	3117						
ASCI	3218						
AST	3029						
ASTON	3001	3158					
				CANAL SATELLITE	3133	3163	5032
				CHAPARRAL	3083		
				CHESS	3133	3150	
				CITYCOM	3043	3066	3084
					3198		
				CLAS OHLSON	3310	3311	5162
				CLATRONIC	3037		
				CLEMENS KAMPHUS	3072		
				CLYDE CABLEVISION	4003		
				CNT	3004		
				COLUMBUS	3059		
				COMAG	3055	3262	3264
					3268	3283	5134
					5136		
				COMCRYPT	4005		
				COMMLINK	3003		
				COMTECH	3042		
				CONDOR	3022	3198	
				CONNEXIONS	3032	3040	
				CONRAD	3198	3233	5092
				CONTEC	3042	3043	
				COSAT	3046		
				COSHIP	3021		
				COUNTRYMAN	5099		
				CROWN	3014		
				CRYPTOVISION	4004		
				CYBERCOM	3007	3008	3017
					3022	3036	3074
					3080	3087	3088
					3112	3130	3147
					3150	3151	3180
					3181	5007	5008
					5023	5046	5055
					5056	5067	5076
					5079		
				CYBERLINK	5072		
				CYBERMAXX	3007	3008	3017
					3022	3036	3050
					3060	3065	3074

	3080	3087	3088	E-TEK	3220		
	3102	3112	3130	EURODEC	4016		
	3147	3150	3151	EUROPHON	3198		
	3180	3181	3202	EUROSAT	3014		
	3204	3205	3206	EUROSKY	3014	3022	3198
	3212	3218	3217		3233	5092	
	5007	5008	5023	EUROSPACE	3052		
	5038	5039	5044	EUROSTAR	3014	3032	
	5046	5055	5056	EVA	3152	3153	
	5067	5076	5079	EXATOR	3000		
CYTRON	3007	3008	3017	FERGUSON	3005	3056	3057
	3022	3036	3050		3084	3166	
	3060	3060	3065	FIDELITY	3010	3012	
	3074	3080	3087	FILMNET	4005		
	3088	3102	3112	FILMNET CABLECRYPT	4005		
	3130	3147	3150	FILMNET COMCRYPT	4005		
	3151	3180	3181	FINLANDIA	3084		
	3202	3204	3205	FINLUX	3023	3058	3062
	3206	3212	3217		3068	3084	3170
	3218	5007	5008	FINNSAT	3042	3166	
	5023	5038	5039	FORCE	3102	3118	3141
	5044	5046	5055		5030		
	5056	5067	5076	FORTE STAR	3054	5016	
	5079			FOXTEL	3259	3260	3299
DAERYUNG	3032				3165	3300	3301
DANSAT	3005				3302	3303	4015
DARTY	5094				4030	4032	4033
D-BOX	3128	3167			4034	4035	
DECCA	3044			FOXTEL IQ	3260	5031	5130
DENVER	3307	3308		FOXTEL IQ2 HD	3306		
DEW	3042			FRACARRO	3126		
DIAMOND	3045			FRANCE SATELLITE/TV	3059		
DIGENIUS	5039			FRANCE TELECOM	5094		
DIGIALITY	3198			FREEBOX	5111		
DIGIFUSION	5041			FREEBOX TV	5106	5111	
DIGIHOME	5149			FREECOM	3000	3070	
DIGIO2	5089			FREE VIEW	5012	5013	5014
DIGIPAL	5127				5015	5018	5021
DIGIQUEST	3021	3066	3227		5022	5024	5025
DIGITAL M SERIE	3277				5028	5033	5040
DILOG	3304				5041	5042	5043
DISKXPRESS	3018	3040			5045		
DITRISTRAD	3046			FTE	3016	3076	
DMA	5133			FUBA	3000	3018	3022
DMT	3007	5007			3025	3032	3033
DNT	3032	3117			3059	3062	3114
DRAKE	3047	3121			3117		
DREAMBOX	3210	5051		FUNK	5101		
DREAM MULTIMEDIA	3210			FUNTACH	3151		
DSTV	3165			GALAXIS	3003	3022	3026
DUAL	3007	3008	3017		3042	3046	3060
	3022	3023	3080		3065	3066	3102
	3087	3088	3130		3146	3147	3165
	3147	3150	3151		3181		
	3180	5007	5008	GALAXY	3018		
	5023			GbSAT	5017		
DURABRAND	5025			GEC	4003		
ECHOSTAR	3019	3048	3049	GERICOM	5010		
	3051	3063	3142	GI	4007	4013	
	3143	3144	3145	GLOBECAST	3221		
	3150	3198	3211	GLOBO	3233	5092	
	5050	5052		GMI	3014		
EINHELL	3000	3003	3012	GOLDSTAR	3070		
	3014			GOODING	3064		
ELEKTA	3004			GOODMANS	3084	5013	5025
ELTA	3000	3022	3046		5048	5148	
	3117			GOODWAY	5165	5166	
EMANON	3000			GRANADA	3023		
EMME ESSE	3022	3072	3084	GRANVISION	3265	3266	
EMITECH	3238			GROTHUSEN	3000	3070	
EMTEC	5070	5071		GRUNDIG	3002	3030	3033
EMTECH	5017				3053	3064	3075
ENIGMA	3276				3084	3110	3116
EP SAT	3084				3148	3165	5021
					5103		

HANDAN	3113	3240		LIFE	3147	5076	
HANSEATIC	3080			LIFESAT	3007	3008	3017
HANTOR	3000	3037			3022	3036	3074
HANURI	3004				3080	3087	3088
HAUPPAUGE	5018	5117			3112	3129	3147
HB	3008	3238	3250		3150	3151	3180
	3251	3252	5017		3181	5007	5008
	5062	5123	5125		5023		
	5126			LIFETEC	3007	3008	3017
HEAD	3279	3280	3284		3022	3036	3050
HELIOCOM	3016				3060	3065	3074
HIRSCHMANN	3033	3068	3069		3080	3087	3088
	3072	3093	3113		3102	3112	3130
	3114	3122	3233		3147	3150	3151
	3239	3242	5092		3180	3181	3202
HISAWA	3037				3204	3205	3206
HITACHI	3084	3103	5025		3212	3217	3218
	5149				5007	5008	5023
HK WHARF CABLE	5161				5038	5039	5044
HOMECAST	5017	5129			5046	5055	5056
HOMESERVER	5133				5067	5076	5079
HUMAX	3066	3091	3278	LITEON	5056		
	3286	3287	3288	LION	3052		
	3146	5045	5144	LOEWE	5164		
	5146	5147		LOGIK	5150		
HUTH	3003	3006	3014	LORENTZEN	3233	5092	
	3037	3046	3072	LORRAINE	3070		
HYUNDAI	3067	5019		LUPUS	3022		
ID DIGITAL	3066			LUXOR	3012	3023	3103
ILO	5056				3114		
IMPERIAL	3126			LYONNAISE	4025		
IMPULSE	4013			MACAB	3166		
INNOVATION	3022	3074	3080	MAGIC TV	5163		
	3087	3126	3147	MALIGNE TV	5094	5109	
	3150	3151	3180	MANHATTAN	3004	3046	3068
INTERSTAR	5017				3084	3121	3194
INTERTRONIC	3014			MARANTZ	3117		
INTERVISION	3046			MARMITEK	3199	4019	5037
IRDETO	3165			MARMITEK OCTOPUS	3208	5048	
ITT/NOKIA	3023	3084	3040	MASCOM	3004		
	3068	3103	3114	MASPRO	3064	3083	3084
JEPSSEN	5017				3122		
JERROLD	4007	4013		MATSUI	3064	3138	5013
JOHANSSON	3037				5025	5043	
JSR	3046			MAXDOME	5138		
JVC	3064	5025	5068	MB	3080		
KABELVISION	4013			MBOX	3016		
KAON	3227			MEDIABOX	3133		
KATHREIN	3033	3043	3076	MEDIACOM	3082		
	3083	3115	3117	MEDIAMARKT	3014		
	3169	3179	3192	MEDIA RECEIVER	5011		
	3196	3246	3256	MEDIASAT	3026	3133	
	5116	5128		MEDION	3007	3008	3017
KOSCOM	3224	5087			3022	3036	3050
KOSMOS	3070	3072	3076		3060	3065	3074
KR	3002				3080	3087	3088
KREILING	3115	3192	3217		3102	3112	3130
	3263				3147	3150	3151
KREISEL MEYER	3033				3180	3181	3202
KYOSTAR	3000				3204	3205	3206
LABGEAR	5022				3212	3217	3218
LASAT	3004	3022	3078		3219	3244	3253
	3129	3130	3131		3285	5007	5039
	3191	3233	3234		5044	5055	5133
	5092	5093			5145	5154	5155
LENCO	3000	3070	3079	MEGA	3117		
LENG	3037			MELITA	4013		
LENNOX	3046			METRONIC	3000	3002	3003
LENSON	3061				3004	3018	3139
LG	3070	5076	5154		3174	3175	3176
	5155				3177	3193	
LIDCOM	5013			METZ	3033		

MICO	5082			OGGLE	5083		
MICRO TECHNOLOGY	3052			OKANO	3014	3072	3076
MICROMAXX	3007	3008	3017	ON-DIGITAL	5026	5027	5035
	3022	3036	3050	OPTEX	3043	3046	3209
	3060	3065	3074		5049		
	3080	3087	3088	OPTUS VISION	3165	3259	4007
	3102	3112	3130		4030		
	3147	3150	3151	ORANGE	5094	5109	5112
	3180	3181	3202	ORBIT	3029		
	3204	3205	3206	ORBITECH	3000		
	3212	3217	3218	ORIGO	3052		
	3219	5008	5023	OSAT	3002		
	5038	5039	5044	OTTO VERSAND	3033		
	5046	5056	5067	PACE	3005	3033	3084
	5075	5076	5079		3095	3119	3123
	5084	5110			3148	3179	3260
MICROSTAR	3007	3008	3017		4018	5014	5026
	3022	3036	3050		5031	5130	
	3060	3065	3074	PACIFIC	3045	5025	
	3080	3087	3088	PACKARD BELL	5064	5072	
	3102	3112	3130	PALCOM	3025	3059	3061
	3147	3150	3151	PALLADIUM	3014	3064	
	3180	3181	3202	PALTEC	3025		
	3204	3205	3206	PANASONIC	3084	3108	3148
	3212	3217	3218		5003	5006	5029
	5007	5008	5023	PANDA	3005	3084	
	5038	5039	5044	PANSAT	3071		
	5046	5055	5056	PANTECH	3155		
	5067	5076	5079	PARDY LIGHT BOX	5102		
MINERVA	3033	3064		PBI	3218		
MITSUBISHI	3033	3084	3138	PHILIPS	3028	3030	3041
MITSUMI	3078				3042	3064	3074
MNET	4005	4015			3075	3084	3089
MORETV	3017	3202	3212		3109	3125	3116
	3244	5038	5079		3117	3133	3138
	5110				3168	3167	3180
MORGAN SYDNEY	3173				3319	4006	5004
MORGANS	3014	3078	3117		5033	5078	5153
	3173			PHOCUS	5065		
MOTOROLA	4007			PHOENIX	3042		
MOVIE TIME	4012			PHONO TREND	3003	3046	3072
MULTICHOICE	3165	4005	4015		3205		
MULTISTAR	3076			PILOTIME	3163		
MULTITEC	3150	3151		PINNACLE	3207	5047	5118
MURATTO	3031	3070			5119	5120	
NAVEX	3037			PIONEER	3133	4008	4009
NEC	3085	3086			5015	5035	5057
NEOTION	3218			POLSAT	3166		
NEUF TELECOM	5108	5115		POLYTRON	3043		
NEUF TV	5108	5115		PREDKI	3037		
NEUHAUS	3026	3046	3061	PREMIER	3133		
NEXTWAVE	3009	3149		PREMIERE	3036	3046	3066
NIKKO	3014				3108	3128	3133
NOKIA	3018	3019	3023		3167	5024	5029
	3040	3068	3084		5033		
	3099	3114	3127	PREMIUM X	3216		
	3128	3167	4014	PRIESNER	3014	3038	
	5024	5027		PRO2	3007	3008	3017
NOMEX	3183				3022	3036	3050
NORDMENDE	3000	3004	3056		3060	3065	3074
	3084	3115	3166		3080	3087	3088
NOOS	4020	4022	4024		3102	3112	3130
	4075	5086	5094		3147	3150	3151
	5105	5112			3180	3181	3202
NOVIS	3037				3204	3205	3206
NOW TV	5113				3212	3217	3218
NTL	4018	4029			5007	5008	5023
NUMERICABLE	4016	5112			5038	5039	5044
OAK	3018				5046	5055	5056
OCEANIC	3045	3052	5112		5067	5079	
OCTAGON	3000	3002	3042	PROCASTER	5055		

PROFI	3079			SELECO	3046		
PROMAX	3084			SHARP	5002		
PROSAT	3003	3126		SIEMENS	3033	3234	5093
PROTEK	3045			SILVA	3070		
PROVISION	3004			SKARDIN	3026	3112	3150
PVP	4013				3236	5049	5100
QUADRAL	3003	3022		SKARSIN	5096		
QUELLE	3012	3033		SKY	3119	3148	3228
QUIERO	3166				3294	5090	
RADIOLA	3117			SKY+	3119	3296	5031
RADIX	3032	3191	3193	SKY+ HD	3228		
	3229	5091		SKY DIGITAL	3119	3148	3294
RAINBOW	3002				5031		
REBOX	5017			SKY ITALIA	3119	3148	
REDIFFUSION	3086			SKYMASTER	3003	3007	3080
REDPOINT	3026				3082	3112	3113
REDSTAR	3022				3150	3151	3152
RFT	3003	3117			3153	3154	3155
RUEFACH	3079				3156	3182	3218
SAB	3217	3224	3225		3220	3235	3236
	3226	3227			3237	3238	3240
SABA	3056	3084	3109		3273	5007	5020
	3120	3126	3129		5049	5085	5095
	3135	3136	3137		5096	5097	5098
	3138				5100	5164	5165
SABRE	3084				3117		
SAGEM	3134	3163	3166	SKYMAX	3233	5092	
	3167	3203	3309	SKYPEX	3218		
	3320	3321	4017	SKYPLUS	3046		
	5032	5042	5086	SKYVISION	3215	3239	3242
	5094	5107		SMART	3265	3270	3271
SAKURA	3042				3272	3273	3274
SALORA	3023	3085	3092		3275	3276	3277
	3095				4023	5081	5097
SAMSUNG	3000	3020	3082		5139	5140	5141
	3322	3323	4021		5142	5143	
	5074	5088			3003	3007	3080
SAT	3010	3029	3031	SM ELECTRONIC	3082	3112	3113
SAT+	3112	3217			3150	3151	3152
SATCOM	3080	3094	3198		3153	3155	3156
SATEC	3084				3182	3218	3220
SATPARTNER	3000	3002	3004		3235	3236	3237
	3037	3070	3072		3238	3240	5007
SCHAUB LORENZ	3227	3238	3250		5020	5049	5091
	3251	3252	5017		5095	5096	5097
	5062	5123	5124		5165	5166	
	5125	5126			3013	3039	3133
SCHNEIDER	3022	3041	3082	SONY	3148	5012	5059
	3087	3147	3150		5060	5061	
	3151	3180			5011		
SCHWAIGER	3004	3006	3007	SONY NETWORK	3014	3056	3078
	3008	3021	3022	SR	3056		
	3024	3027	3034	STARBOX	3000		
	3043	3080	3084	STAR TRAK	3150		
	3283	3088	3090	STARLAND	3037		
	3129	3130	3131	STARRING	3000	3002	3022
	3137	3139	3140	STRONG	3040	3070	3111
	3141	3146	3147		3126	3165	
	3149	3151	3162		4012		
	3178	3191	3192	STS	3014		
	3194	3196	3213	SUMIDA	3014		
	3214	3215	3227	SUNSTAR	3014	3078	3095
	3229	3233	3234	TANDBERG	3166		
	3241	3262	3264	TANDY	3002		
	3267	5007	5023	TANTEC	3059	3061	3084
	5036	5080	5091	TARGA	3245	5075	5076
	5092	5093	5104		5114		
	5134	5136			3044		
SCIENTIFIC ATLANTA	4010	4011		TATUNG	3007	3008	3017
SEEMANN	3032	3014	3026	TCM	3022	3036	3074
SEG	3000	3022	3037		3080	3087	3088
	3080	3107	3192		3112	3130	3147
	3195						

	3150	3151	3180		3313	3314	3315
	3181	5007	5008		3316	3317	3318
	5023	5063	5077	TVONICS	5150		
	5152			UNIDEN	3101		
TECHNIHALL	3011			UNISAT	3014	3042	
TECHNIKA	5149			UNITED	4013		
TECHNISAT	3032	3055	3061	UNITOR	3018	3037	
	3082	3096	3097	UNIVERSUM	3033	3058	3064
	3133	3184	3254		3068	3233	5092
	5127			UPC	4020	4024	4026
TECHNOMATE	3022	3035			5086	5094	5105
TECHNOTREND	3213	3227	3241	VANTAGE	3282		
	3261	5104	5135	VARIOSAT	3033		
TECO	3014	3078		VECTOR	3052		
TEINNER	3172	3173		VENTANA	3117		
TELASAT	3198			VERSATEL	5088		
TELE+1	4005			VIA DIGITAL	3132		
TELEFONICA	5132			VIA SAT	3132		
TELEFUNKEN	3000	3084	3124	VIRGIN MEDIA	4018		
	3129	3130	3131	VISIONETICS	4027		
	3138			VISIOSAT	3037	3046	3150
TELEKA	3002	3014	3032		3157	3158	3159
	3198				3160	3161	4006
TELEMASTER	3004			VIVANCO	3185	3291	5035
TELEPIU	4005			VORTEC	3000		
TELESAT	3080			V-TECH	3029	3031	3089
TELESTAR	3061	3133	3218		3103		
TELEVES	3084	3172	3173	WEVASAT	3084		
	5017			WEWA	3084		
TELEWIRE	3046			WHARFEDALE	5149		
TELEWEST	4013	4018		WINERSAT	3037		
TEN HAAFT	3017			WISI	3029	3031	3032
TEVION	3007	3008	3017		3033	3084	3100
	3022	3036	3050		3104	3105	3106
	3060	3065	3074		3161	3186	3187
	3080	3087	3088		3188	3189	3190
	3102	3112	3130	WITTENBERG	3010		
	3147	3150	3151	WOORISAT	3004		
	3180	3181	3202	WORLDSAT	3192	5017	
	3204	3205	3206	WYSI	3233	5092	
	3212	3217	3218	XTREME	3227		
	3220	5007	5008	YAUKMO	5055		
	5023	5038	5039	YUNG FU	5098		
	5044	5046	5054	ZEHNDER	3004	3018	3022
	5055	5056	5066		3031	3076	3107
	5067	5076	5079		3192	3193	3196
THOMSON	3021	3056	3073		3217	3218	3265
	3084	3124	3132		3266		
	3133	3134	3138	ZINWELL	3066		
	3164	3166	3233	ZODIAC	3002		
	4028	5004	5005				
	5009	5028	5034				
	5069	5092	5105				
THORENS	3045			<b>DVD</b>			
THORN	3005	3057	3084	<b>Model</b>	<b>Code</b>		
TIOKO	3043			ACOUSTIC SOLUTION	6020	6053	
TIVO	5004			AEG	6003	6080	
TONBURY	3038	3235	5095	AFREEY	6056		
TONNA	3046	3084	3112	AIRIS	6027		
TOPFIELD	3077	3081	3082	AIWA	6047	6053	
	3247	3248	3249	AKAI	6003	6020	6039
	5020	5121	5122		6052	6080	6205
TOP UP TV	5026	5027	5050	AKASHI	6016		
TOSHIBA	5058	5073		ALBA	6020	6021	6027
TPS	3134				6040	6051	6054
TPS ADSL	5094	5108	5109	ALL-TEL	6003		
TPS PLATINUM	3243			AMES	6053		
TRIAD	3029	3031	3070	AMSTRAD	6020		
	3100			AMW	6178	6179	
TRIASAT	3062			ANABA	6146		
TRIAx	3033	3061	3129	ANSONIC	6026		
	3171	3181	3312				

APEX	6027	6054	6060		6191	6192	6193
	6097	6099	6107		6194	6195	6196
	6134	6206			6233	6234	
ARENA	6109			CYTRON	6000	6004	6005
ASPIRE	6137				6008	6009	6010
A-TREND	6017				6011	6012	6013
AUDIOSONIC	6052	6187			6014	6015	6022
AUDIOVOX	6127				6026	6028	6041
AXION	6127				6042	6043	6045
B&K	6163				6050	6075	6079
BAIER	6019				6080	6081	6082
BAZE	6027				6083	6084	6085
BEKO	6189				6086	6087	6088
BLACK DIAMOND	6020				6089	6090	6091
BLAUPUNKT	6054				6092	6109	6110
BLU-RAY	6045	6204	6223		6115	6117	6118
	6224	6225	6229		6144	6191	6192
	6254				6193	6194	6195
BLUE NOVA INTERNAT	6176				6196	6233	6234
BLUE SKY	6020	6027	6043	CYBERVISION	6249		
	6045			DAEWOO	6017	6023	6024
BOMAN	6021	6080			6025	6050	6111
BRANDT	6030	6032	6046		6150	6156	
BRITANIA	6253			DANSAI	6021		
BROKSONIC	6106	6152		DAYTRON	6111		
BUSH	6020	6026	6051	DCE	6026		
	6052	6054		DENON	6034	6059	
CAMBRIDGE	6046			DENVER	6051	6080	6176
CELESTIAL	6027			DENZEL	6062		
CENTREX	6027			DESAY	6043		
CENTRIOS	6117	6136	6139	DIAMOND	6011	6043	
	6140			DIGIFRAME	6115		
CENTRON	6117			DIGIHOME	6020		
CENTRUM	6112	6113	6114	DIGITOR	6052		
	6016	6020		DIGITREX	6027		
CINETEC	6020			DIGITRON	6056		
CINEVISION	6045			DIGIX	6147		
CLAS OHLSON	6242	6243	6260	DIK	6026		
	6261	6262	6263	DISNEY	6009	6088	
	6264			DIVIDO	6050		
CLASSIC	6053			DIVX	6045	6117	
CLATRONIC	6027	6080		DK DIGITAL	6026		
CMI	6109			DMTECH	6003	6021	
COBY	6002	6027	6102	DRAGON SYSTEM	6026		
	6131	6132	6133	DUAL	6000	6003	6004
	6176				6005	6007	6008
CONTEL	6080	6245			6010	6011	6012
CRITERION	6014				6013	6014	6015
CROWN	6043	6052			6020	6021	6022
C-TECH	6010				6026	6028	6041
CURTIS	6133	6135			6042	6043	6045
CYBERCOM	6000	6004	6005		6053	6062	6075
	6009	6010	6011		6109	6110	6118
	6012	6013	6015		6141	6168	
	6008	6026	6042	DURABRAND	6003	6026	6045
	6043	6075	6110		6118	6208	6209
	6115	6117	6118		6210	6211	
CYBERHOME	6017	6098	6169	DVD 1024	6258		
	6198			E-BENCH	6011		
CYBERLINK	6220			ELTA	6003	6035	6052
CYBERMAXX	6000	6004	6005		6080		
	6008	6009	6010	ELTAX	6176		
	6011	6012	6013	EMERSON	6009	6045	6050
	6014	6015	6022		6182		
	6026	6028	6041	ENCORE	6056		
	6042	6043	6045	ENZER	6062		
	6075	6079	6080	ESA	6141		
	6081	6082	6083	EUROLINE	6080		
	6084	6085	6086	FARENHEIT	6145		
	6087	6088	6089	FERGUSON	6043		
	6090	6091	6092	FINLUX	6021	6027	6045
	6109	6110	6115	FINTEC	6020		
	6117	6118	6144				



FIRSTLINE	6043			LIFETEC	6000	6004	6008
FISHER	6048				6009	6010	6011
FUNAI	6009				6012	6013	6014
GE	6054				6015	6022	6026
GERICOM	6189				6028	6041	6042
GOLDEN SPHERE	6011				6043	6045	6075
GOLDSTAR	6045	6093	6157		6079	6081	6082
GOODMANS	6003	6020	6021		6083	6084	6085
	6043	6052			6086	6087	6088
GO-VIDEO	6008	6037	6053		6089	6090	6091
	6121	6156	6184		6109	6110	6115
	6186				6117	6118	6144
GPX	6096				6145	6191	6192
GRADIENTE	6043	6251	6252		6193	6194	6195
GRAETZ	6062				6196	6233	6234
GRAN PRIX	6026			LIMIT	6011		
GRANDIN	6027			LINN	6006		
GRUNDIG	6003	6020	6040	LITEON	6144	6167	6181
	6043	6046	6048		6184		
	6050	6055		LODOS	6020		
H&B	6013	6020		LOEWE	6040	6045	
HB	6212	6218		LOGIX	6021	6050	
HAAZ	6011	6012		LUMATRON	6002	6012	
HANSEATIC	6003	6021	6045	LUXMAN	6037		
HARMAN KARDON	6065			LUXOR	6020		
HCM	6080			MAGNAVOX	6020	6032	6040
HD-DVD	6045	6204	6223		6049	6100	6164
	6224	6225	6226		6165	6166	
	6254			MANHATTAN	6020	6050	
HE	6053			MARANTZ	6032	6040	6045
HITACHI	6037	6038	6057		6049	6166	6202
	6062			MARK	6020		
HITEKER	6027			MASTEC	6005		
HOHER	6026			MATSUI	6020	6027	6043
HOME ELECTRONICS	6053			MAXDORF	6080		
HOMITA	6119	6120	6121	MAXIM	6001	6020	
	6122	6123		MBO	6052	6053	6066
HOYO	6062			MEDIENCOM	6012		
HYUNDAI	6021			MEDION	6000	6004	6005
ILO	6144				6008	6009	6010
INITIAL	6054				6011	6012	6013
INTEGRA	6044				6014	6015	6021
INTERTRONIC	6079	6080	6118		6022	6026	6028
JATON	6062				6041	6042	6043
JBL	6065				6045	6075	6079
JDB	6053				6080	6081	6082
JVC	6031	6032	6070		6083	6084	6085
	6074	6149	6183		6086	6087	6088
	6197				6089	6090	6091
JWIN	6199	6206			6092	6109	6110
KARCHER	6021				6115	6117	6118
KAWASHI	6003				6144	6174	6191
KENDO	6020	6026	6109		6192	6193	6194
KENNEX	6020				6195	6196	6231
KENWOOD	6034	6063			6232	6233	6234
KISS	6062				6256	6257	
KLH	6054			MEMOREX	6009	6026	6106
KONKA	6094	6095		MERIDIAN	6032		
KOSS	6028	6043		METZ	6020	6038	6108
LASONIC	6011			MICROMAXX	6000	6004	6005
LAWSON	6011	6050			6008	6009	6010
LECSON	6046				6011	6012	6013
LENCO	6020	6026	6043		6014	6015	6022
	6247				6026	6028	6041
LENOXX	6016	6052	6116		6042	6043	6045
LG	6045	6093	6157		6075	6079	6080
	6233	6255	6256		6081	6082	6083
	6257				6084	6085	6086
LIFE	6042	6043	6086		6087	6088	6089
	6233	6234			6090	6091	6092

	6109	6110	6115	PORTLAND	6052		
	6117	6118	6144	PRINZ	6026		
	6191	6192	6193	PRISM	6005		
	6194	6195	6196	PRO2	6000	6004	6005
MICROMEGA	6233	6234			6008	6009	6010
MICROSOFT	6040				6011	6012	6013
MICROSTAR	6069	6241			6014	6015	6022
	6000	6004	6005		6026	6028	6041
	6008	6009	6010		6042	6043	6045
	6011	6012	6013		6075	6079	6080
	6014	6015	6022		6081	6082	6083
	6026	6028	6041		6084	6085	6086
	6042	6043	6045		6087	6088	6089
	6075	6079	6080		6090	6091	6092
	6081	6082	6083		6109	6110	6115
	6084	6085	6086		6117	6118	6144
	6087	6088	6089		6191	6192	6193
	6090	6091	6092		6194	6195	6196
	6109	6110	6115	PROCASTER	6091		
	6117	6118	6144	PROLINE	6003	6027	6043
	6191	6192	6193		6046	6067	
	6194	6195	6196	PROSCAN	6069		
	6233	6234		PROSON	6020		
MINATO	6019			PROSONIC	6002	6011	6019
MINERVA	6050			PROVIEW	6174		
MINTEK	6054			PROVISION	6051	6176	
MIRROR	6019			QUADRO	6114		
MITSUBISHI	6020	6036		QUARTEK	6200		
MONYKA	6062			RADIONETTE	6045		
MT LOGIC	6187			RAITE	6062		
MUSTEK	6053			RCA	6054	6069	
MXONDA	6043			REDSTAR	6080	6150	
MYSTRAL	6026			RELISYS	6081	6109	
NAD	6045	6064		REOC	6011		
NAKAMICHI	6068			REX	6016		
NEC	6045			ROADSTAR	6020	6052	6053
NEOTEK	6056			RONIN	6067		
NEUFUNK	6062			ROTEL	6031		
NEVIR	6026			ROWA	6054	6108	
NEXXTECH	6117	6139	6140	RTL	6109		
	6141	6245		SABA	6030	6043	6101
NORCENT	6002	6129	6130	SAIVOD	6026		
	6133	6167		SALORA	6045		
	6026			SAMPO	6011	6056	6081
NORDMENDE	6019				6109	6176	
NORIKO	6212			SAMSUNG	6008	6037	6105
OCEANIC	6019	6032			6148	6175	6228
OKANO	6052				6229	6230	6238
OMNI	6016			SANSUI	6011	6106	
ONIX	6044	6045		SANYO	6003	6020	6048
ONKYO	6038	6108			6185		
OPTIMUS	6005	6106		SCAN	6050		
ORION	6043			SCHAUB LORENZ	6080	6212	6218
ORITRON	6003	6020	6026	SCHNEIDER	6003	6020	6021
PACIFIC	6124	6125	6177		6022	6026	6043
PACKARD BELL	6220				6050	6080	
	6027			SCHWAIGER	6019		
PALSONIC	6034	6071	6073	SCIENTIFIC LABS	6011		
PANASONIC	6155	6159	6223	SCOTT	6027	6043	
PANDA	6021			SEG	6011	6020	6062
PHILCO	6250			SHARP	6020	6041	6064
PHILPS	6009	6032	6040		6180	6254	
	6049	6154	6164	SHERWOOD	6061		
	6165	6166	6203	SHINCO	6054		
	6239	6240	6248	SHINSONIC	6054		
PHOCUS	6188	6189		SILVA	6080		
PHONOTREND	6102			SILVA SCHNEIDER	6026		
PIONEER	6038	6108	6153	SILVERCREST	6011	6213	6214
	6161	6162	6207		6215	6216	
	6224	6225		SINGER	6011	6052	
POLAROID	6134	6142					

				DVD-R			
				Model	Code		
SKYMASTER	6052	6053		APEX	6097		
SM ELECTRONIC	6011	6052	6053	ARENA	6109		
SMART	6020	6050		ASPIRE	6137		
SONY	6033	6072	6170	BLUE NOVA INTERNAT	6176		
	6171	6172	6173	CENTRIOS	6136		
	6204			CMI	6109		
SOUNDMASTER	6011			COBY	6176		
SOUNDMAX	6011			CYBERCOM	6109		
SOUNDSTORM	6000			CYBERHOME	6098		
SOUNDWAVE	6021			CYBERMAXX	6081	6091	6092
STANDARD	6043				6109	6144	6196
STRONG	6020				6233		
SUNGALE	6138			CYTRON	6081	6091	6092
SUPERVISION	6052	6053			6109	6144	6196
SVA	6019				6233		
SYLVANIA	6009			DENVER	6176		
SYNN	6011			DUAL	6109		
TANDBERG	6020			ELTAX	6176		
TANGENT	6176			EMERSON	6182		
TARGA	6027	6077	6093	GO-VIDEO	6053	6184	6186
	6144	6157	6217	HITACHI	6057		
	6231	6233	6237	HB	6212		
TCM	6000	6003	6004	ILO	6144		
	6005	6008	6009	JVC	6183	6197	
	6010	6011	6012	KENDO	6109		
	6013	6014	6015	LG	6093		
	6022	6026	6028	LIFE	6233		
	6041	6042	6043	LIFETEC	6081	6091	6092
	6075	6080	6086		6109	6144	6196
	6109	6110	6115		6233		
	6117	6118	6189	LITEON	6144	6181	6184
	6235			LUMATRON	6176		
THETA DIGITAL	6038			MAGNAVOX	6164	6165	
THOMSON	6029	6030	6069	MEDION	6081	6091	6092
	6201				6109	6144	6196
TINY	6176				6233		
TOKAI	6062	6080		MICROMAXX	6081	6091	6092
TOKIWA	6050				6109	6144	6196
TOSHIBA	6032	6106	6158		6233		
	6226	6227	6236	MICROSTAR	6081	6091	6092
	6259				6109	6144	6196
TRANSCONTINENTS	6026	6176			6233		
TRANSONIC	6027				6081	6091	6092
TREDEX	6126				6109	6144	6196
TRUTECH	6198				6233		
UMAX	6052			MUSTEK	6053		
UNITED	6003	6018	6027	OCEANIC	6212		
	6080			PACKARD BELL	6125	6177	
UNIVERSUM	6003	6020	6045	PANASONIC	6073		
VENTURER	6003			PHILIPS	6164	6165	6203
VESTEL	6020	6244			6240		
VIETA	6050			PHOCUS	6188		
VOXSON	6026	6052	6053	PIONEER	6162	6207	
WALKVISION	6054			PRO2	6081	6091	6092
WELKIN	6026				6109	6144	6196
WELLTECH	6219	6221	6222	PROVISION	6176		
WESTAR	6020			RTL	6109		
WHARFEDALE	6011	6019	6046	SAMPO	6126		
	6056			SAMSUNG	6175	6228	
WILSON	6026			SANYO	6185		
X-BOX	6069			SCHAUB LORENZ	6212		
XENIUS	6028	6043		SHARP	6180		
XLOGIC	6011			SONY	6171	6172	6173
XMS	6080			TANGENT	6176		
YAKUMO	6027	6091	6206	TARGA	6077	6093	6144
YAMAHA	6034	6040	6058		6231	6233	6237
	6164	6165	6246	TCM	6114		
	6052	6062	6067	TELEDEVICE	6176		
YAMAKAWA	6053						
YUKAI	6053						
ZENITH	6045	6093					

TEVION	6076	6077	6081	<b>DVD/VCR Combo</b>		
	6091	6092	6109			
	6144	6190	6196	<b>Model</b>	<b>Code</b>	
	6233					
THOMSON	6029	6030	6201	APEX	6134	
TINY	6176			BROKSONIC	6106	6152
TOSHIBA	6032	6158	6227	CINEVISION	2025	6045
	6259			CYBERCOM	2025	2092 6045
TRANSCONTINENTS	6176			CYBERMAXX	2025	2092 6045
YAKUMO	6091				6082	6092
YAMAHA	6164	6165		CYTRON	2025	2092 6045
ZENITH	6093				6082	6092

### TV/DVD Combo (DVD&TV)

Model	Code			Model	Code		
AKAI	1219	6205		FUNAI	2001	2093	
AUDIOSONIC	1090	6187		GO-VIDEO	2092	2095	2110
BEKO	6189			GOLDSTAR	2025	2096	
BROKSONIC	6106			HITACHI	2001	2097	
CYBERCOM	1210	1228	1275	JVC	2098		
	6013	6110		LG	2025	2096	2102
CYBERMAXX	1210	1228	1275	LIFETEC	2025	2092	2096
	1276	6013	6080		6082	6092	
CYTRON	1210	1228	1275	MAGNAVOX	2053	2103	
	1276	1279		MEDION	2025	2092	2096
DUAL	1210	1228	1275		2101	6082	
	1276	6013		MICROMAXX	2025	2092	2096
DURABRAND	1228	1266	1267		2101	6082	
	1268	1269	1275	MICROSTAR	2025	2092	2096
	6208	6209	6210		2101	6082	
	6211			PANASONIC	2109		
H&B	1228	6213		PHILIPS	2053	2108	
HB	1263	6212		PIONEER	2112		
GERICOM	1244			POLAROID	2105		
INTERTRONIC	1278			PRO2	2025	2092	2096
LIFETEC	1210	1228	1275		2101	6082	
	1276	1278	6013	SAMSUNG	2092	2106	
MEDION	1210	1228	1275	SANYO	2027	6048	
	1276	1278	6013	SILVERCREST	2025		
MEMOREX	6106			SONY	2099		
MICROMAXX	1210	1228	1275	SYLVANIA	2001	2093	
	1276	1279	6080	TARGA	2025	2096	2102
MICROSTAR	1210	1228	1275		2111		
	1276	1278	6013	TCM	2025	2092	2096
MT LOGIC	1090	6187		TEVION	2101	6082	
OCEANIC	1239	1263		TOSHIBA	2094		
ORION	1277			ZENTH	2025	2096	
PHILIPS	1181	6009					
PRO2	1210	1228	1275				
	1276	1278	1279				
PROVIEW	1274						
SANSUI	1277						
SCHAUB LORENZ	1213	1239					
TCM	1210	1228	1238				
	1275	1276	1279				
TEVION	1210	1228	1244				
	1275	1276	1278				
	1279						
TOSHIBA	1277						
VESTEL	1066	1215					

### Media Center PC

Model	Code
MCE	6241
MICROSOFT	6241
MSVISTA	6241

## Home Cinema Systems (DVD&AUDIO)

Model	Code		
AIWA	6047		
AMW	6179		
CENTRUM	6113		
COBY	6133		
CRITERION	6014	8049	
CURTIS	6133		
CYBERCOM	6004	6014	6042
	8049		
CYBERMAXX	6004	6014	6042
	6191	6194	6234
	8049		
CYTRON	6004	6014	6042
	6191	6194	6234
	8049		
DUAL	6004	6014	6042
	8049		
DURABRAND	6045		
FISHER	6048		
JVC	6074	6149	
KOSS	6043		
LENCO	6247		
LENOXX	6116		
LG	6157	6255	
LIFE	6234		
LIFETEC	6004	6014	6042
	6191	6194	6234
	8049		
MEDION	6004	6014	6042
	6191	6194	6234
	8049		
MICROMAXX	6004	6014	6042
	6191	6194	6234
	8049		
MICROSTAR	6004	6014	6042
	6191	6194	6234
	8049		
NORCENT	6133		
ONKYO	6160		
PANASONIC	6159		
PHILIPS	6040	8022	
PIONEER	6153	6161	
PRO2	6004	6014	6042
	6191	6194	8049
SAMSUNG	5156	6105	
SONY	6170		
TARGA	2111	6045	6157
TCM	6004	6014	8049
TEVION	6004	6014	6042
	6078	6103	6104
	6191	6194	6234
	8049		
WELLTECH	6219	6221	

## CD Player

Model	Code		
ADCOM	7109		
AIWA	7072	7110	7111
	7112		
AKAI	7113	7114	7115
ALBA	7116		
ARCAM	7057		
BESTAR	7117		
BSR	7118		
BUSH	7000		
CARRERA	7002		
CLASSIC	7090		
CONDOR	7118		
CYBERCOM	7003	7007	7013
	7063	7064	7065
	7066	7067	7068
	7086	7087	7088
	7090	7091	7096
	7097		
CYBERMAXX	7003	7007	7013
	7063	7064	7065
	7066	7067	7068
	7086	7087	7088
	7090	7091	7096
	7097		
CYTRON	7003	7007	7013
	7063	7064	7065
	7066	7067	7068
	7086	7087	7088
	7090	7091	7096
	7097		
DENON	7004	7005	
DUAL	7003	7007	7013
	7063	7064	7065
	7066	7067	7068
	7069	7086	7087
	7088	7109	
E-BENCH	7092		
ELTA	7006	7007	7027
	7066	7120	
EMERSON	7109	7117	
FISHER	7008		
GENEXXA	7009	7010	7011
	7013	7014	7015
	7117		
GOLDSTAR	7002		
GOODMANS	7016	7017	
GRUNDIG	7018	7031	7032
	7057		
HARMAN KARDON	7019		
HITACHI	7020	7021	7063
	7064	7065	7066
	7109		
INNOVATION	7067	7068	
JVC	7001	7022	
KENWOOD	7008	7023	7024
	7025	7124	
LIFE	7100		
LIFETEC	7003	7007	7013
	7063	7064	7065
	7066	7067	7068
	7086	7087	7088
	7090	7091	7096
	7097	7100	
LG	7002		
LINN	7057		
LUXMAN	7026		
MAGNUM	7063	7064	7065
	7066	7067	7068



YAMAHA	8017	8031	8044	TCM	8012	8015	8030
	8045	8046	8091		8074	8075	8076
	8092	8113	8114		8080	8081	8084

### Audio Tape Player

Model	Code		
GRUNDIG	8014		
KENWOOD	8040		
NAD	8069		
SHERWOOD	8056		
SONY	8034		
TECHNICS	8041	8051	
THOMSON	8095		
YAMAHA	8017	8046	

### Mini HiFi System

Model	Code		
AIWA	8047	8048	
CYBERCOM	8015	8030	8074
	8075	8080	8081
	8100	8102	
CYBERMAXX	8015	8030	8074
	8075	8076	8077
	8080	8081	8100
	8102		
CYTRON	8015	8030	8074
	8075	8076	8077
	8080	8081	8100
	8102		
DUAL	8015	8030	8068
	8080	8081	8100
	8102		
E-BENCH	8076		
ELTA	8011	8030	
GRUNDIG	8016		
INSIGNIA	8021		
INTERTRONIC	8076		
LIFE	8076	8084	8110
LIFETEC	8015	8030	8074
	8075	8076	8077
	8080	8081	8084
	8100	8102	8110
MEDION	8015	8019	8021
	8030	8074	8075
	8076	8077	8080
	8081	8084	8100
	8102	8110	
MICROMAXX	8015	8030	8074
	8075	8076	8077
	8080	8081	8100
	8102		
MICROSTAR	8015	8030	8074
	8075	8076	8077
	8080	8081	8100
	8102		
PIONEER	8032		
PRO2	8015	8030	8074
	8075	8076	8077
	8080	8081	8100
	8102		
SAMSUNG	8043		
SHARP	8061		
SILVERCREST	8076	8089	8090
	8109		
SONY	8029		

TEVION

WELLTECH

### LD

Model	Code	
DENON	8000	8001
GRUNDIG	8001	
MITSUBISHI	8001	
NAD	8001	
PIONEER	8001	
TELEFUNKEN	8001	
THORN	8002	

## ***Warranty and Support***

This product is guaranteed against faulty materials and workmanship for a period of 1 year from the date of purchase. The obligation to the purchaser under this warranty is limited to servicing the unit and replacing defective parts when the product is returned freight prepaid to the retailer. This warranty becomes void if the product has been tampered with, damaged by accident, damaged in any other way by improper use or has been purchased second hand. All production orders have quality inspections. In the unlikely event of a deficiency, please contact the retailer from whom this product was purchased. Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and for compensation for any reasonably foreseeable loss or damage. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure.



**skandia**

Skandia Antennas Pty Ltd  
131 Wedgewood Road  
Hallam Victoria 3803  
[www.antennawarehouse.com.au](http://www.antennawarehouse.com.au)  
1300 788 466

830-0600-5001